

# SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 45A

| Product designation<br>Product type designat | ion                  |  |                | Soft Starter<br>ADXB  |
|--|----------------------|--|----------------|---|
| Motor type                                   |                      |  |                | Asynchronous  |
| Electrical features                          |                      |  |                | three phase   |
| Supplies voltage                             |                      |  |                |   |
|  |                      | Type of system<br>Rated supply voltage<br>auxiliary supply voltage (Us)<br>Rated frequency | V<br>Hz        | Three phase<br>208500VAC<br>208240VAC<br>50/60  |
| Rated starter current I                      | e                    |  | Α              | 45  |
| Rated motor power                            | IEC ratings (T≤40°C) | 230VAC<br>400VAC<br>500VAC   | kW<br>kW<br>KW | 11<br>22<br>30  |
|  | UL ratings (T≤40°C)  | 330.7.6  |                |   |
|  | 3 ( 1 1)             | 220-240VAC<br>380-415VAC<br>440-480VAC   | HP<br>HP<br>HP | 15<br>25<br>30  |
| Number of controlled                         | phases               |  | Nr.            | 3   |
| Built-in bypass                              |                      |  |                | Yes   |
| Cooling System Programming interface         | e                    |  |                | Natural   |
| Display                                      |                      |  |                | Backlit LCD 2x16 character  |
| Programming with NF                          | C technology         |  |                | No  |
| Optical port Startup and stop settir         | age                  |  |                | No  |
| Startup method                               | igs                  |  |                | Torque or voltage ramp with current limitation  |
| Stop method                                  |                      |  |                | Torque ramp,<br>voltage ramp,<br>free-wheel stop  |
| Braking method                               |                      |  |                | DC dynamic with external relay  |
| Protections                                  |                      |  |                | V 16  |
| Auxiliary supply protect                     |                      |  |                | Voltage too low  No power, phase loss, phase sequence, frequency out of limits, minimum and maximum voltage |





51ADX0045B

# SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 45A

| Motor protection                             |                         |     | Overload at starting (trip class 2, 10A, 10, 15, 20, 25, 30, 35 and 40), overload during running (trip class 2, 10A, 10, 15, 20, 25 and 30), locked rotor, current asymmetry, minimum torque (dry run),  Overcurrent, overtemperature, |
|--|-------------------------|-----|--|
| Starter protection                           |                         |     | bypass failure,<br>phase shorted,<br>temperature<br>sensor fault,<br>maintenance<br>request  |
| Functions                                    |                         |     |  |
| Built-in bypass                              |                         |     | 3  |
| Built-in display and keypad                  |                         |     | Yes  |
| Languages                                    |                         |     | Yes  |
| View measurements                            |                         |     | 4  |
| Torque control                               |                         |     | Yes  |
| Adjustable current limit                     |                         |     | Yes  |
| Dynamic braking                              |                         |     | Yes  |
| Kick Start function                          |                         |     | Yes  |
| Motor overload electronic protection         |                         |     | Yes  |
| Motor protection PTC input                   |                         |     | Yes  |
| Protection against phase loss                |                         |     | Yes  |
| Protection against phase inversion           |                         |     | Yes  |
| Protection against locked rotor              |                         |     | Yes  |
| Protection against thyristor overtemperature |                         |     | Yes  |
| Protection against low load                  |                         |     | Yes  |
| Programmable alarm                           |                         |     | Yes  |
| Digital inputs                               |                         |     | Yes  |
| Analog inputs                                |                         |     | Yes  |
| Digital outputs                              |                         |     | Yes  |
| Analog output                                |                         |     | Yes  |
| Monitoring communication                     |                         |     | Yes  |
| Optical port for programming                 |                         |     | RS323  |
| Event log                                    |                         |     | No   |
| Motor hour counter                           |                         |     | Yes  |
| Startup counter                              |                         |     | Yes  |
| Clock calendar                               |                         |     | Yes  |
| Remote external keypad                       |                         |     | Yes  |
| Plug-in version                              |                         |     | Optional   |
| Input and Output                             |                         |     |  |
| Digital inputs                               |                         |     |  |
|  | Number of digital input | Nr. | 3 (2 digital inputs<br>+ 1 digital/analog<br>input)  |





# SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 45A

| Analog inputs   | Digital input type  Digital input functions | 24VDC (no need for external feeder) 1 input for start, 1 input programmable (stop, free-wheel stopping, external alarm, motor preheat, local control, alarms inhibit, manual resetting of motor thermal protection, keypad lock, second moto |
|-----------------|---|--|
| Analog inputs   | Number of analog input                      | Nr. 1 (digital/analog)<br>0-10VDC (0-  |
|                 | Analog input type                           | 20mA with external resistor 500Ω)  |
| Divited autouts | Analog input functions                      | Motor protection via PTC probes, acceleration and/or deceleration ramp via analog input, analog input thresholds for motor starting and stopping, analog input thresholds for programmable relay enable                                      |
| Digital outputs | Number of digital output                    | Nr. 4  |
|                 | Digital output arrangement                  | 3 x 1 NO (SPST)<br>+ 1 C/O (SPDT)<br>Ratings: 5A<br>250VAC AC1, 2A<br>250VAC AC15  |
| Analog outputs  | Digital output functions                    | C/O output for global alarm, 3 x 1NO outputs programmable (OFF, motor powered, up to speed, braking, current limit, service required, cascade starting, programmable input thresholds, alarm Axx)  |

51ADX0045B





### SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTOR, 45A

Number of analog output Nr.

0...20mA,

Analog output type

Analog output functions

4...20mA (0...10V with external resistor  $500\Omega$ ) Current, torque, motor thermal

status, power

factor and active

power

#### Ambient conditions

#### Temperature

Operating temperature

°C min -10

+55°C (with current derating max

>45°C of 1.5%/ °C)

Storage temperature

°C min -30

°C +70 max 1000 without


derating (over Max altitude m 1000mt with current derating of 0.5%/100m)

95% without Relative humidity % condensation or dripping

Pollution degree 3

## Housing

| . re dien ig            |    |                 |
|-------------------------|----|-----------------|
| Mounting                |    | Screw-fixing    |
| IP degree of protection |    | IP20            |
| Dimensions (W x H x D)  | mm | 157 x 372 x 223 |
| Weight                  | Kg | 9.24            |



| TYPE      | A           | В            | С           | D           | E            |
|-----------|-------------|--------------|-------------|-------------|--------------|
| ADX 0017B | 157 (6.18") | 372 (14.64") | 223 (8.78") | 131 (5.16") | 357 (14.05") |
| ADX 0030B | 157 (6.18") | 372 (14.64") | 223 (8.78") | 131 (5.16") | 357 (14.05") |
| ADX 0045B | 157 (6.18") | 372 (14.64") | 223 (8.78") | 131 (5.16") | 357 (14.05") |
| ADX 0060B | 157 (6.18") | 534 (21.02") | 250 (9.84") | 132 (5.20") | 517 (20.35") |
| ADX 0075B | 157 (6.18") | 534 (21.02") | 250 (9.84") | 132 (5.20") | 517 (20.35") |
| ADX 0085B | 157 (6.18") | 534 (21.02") | 250 (9.84") | 132 (5.20") | 517 (20.35") |
| ADX 0110B | 157 (6.18") | 584 (22.99") | 250 (9.84") | 132 (5.20") | 567 (22.32") |
| ADX 0125B | 157 (6.18") | 584 (22.99") | 250 (9.84") | 132 (5.20") | 567 (22.32") |

#### Certifications and compliance

#### Compliance

#### IEC/EN 60947-1



## 51ADX0045B

SOFT STARTER, ADX... TYPE, FOR SEVERE DUTY (STARTING CURRENT 5•IE). WITH INTEGRATED BY-PASS CONTACTÓR, 45A

IEC/EN 60947-4-2

Certificates

EAC

ETIM classification

EC000640 - Soft ETIM 8.0

starter