

ADXNB025 SOFT STARTER, ADXNB... TYPE, BASIC VERSION, WITH INTEGRATED BY-PASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 25A



Product designation Product type designation			Soft starter basic ADXNB
Motor type			Asynchronous three phase
Electrical features			
Supplies voltage			
	Type of system		Three phase
	Rated supply voltage	V	208600VAC
	auxiliary supply voltage (Us)		100240VAC
	Rated frequency	Hz	50/60
Rated starter current le		А	25
Rated motor power			
IEC ratings (T≤40°C)			
	230VAC	kW	5.5
	400VAC	kW	11
	500VAC	KW	15
UL ratings (T≤40°C)			
	220-240VAC	HP	7.5
	380-415VAC	HP	10
	440-480VAC	HP	15
	550-600VAC	HP	20
Number of controlled phases		Nr.	2
Built-in bypass			Yes
Cooling System			Natural or forced
			(optional)
Rated insulation voltage Ui		V	600
Programming interface			
			Settings: starting voltage,
Potentiometer			acceleration
			ramp,
			deceleration
Display			ramp No
Programming with NFC technology			No
Optical port			No
Startup and stop settings			
Startup method			Voltage ramp
· · ·			Voltage ramp or
Stop method			free-wheel stop
Acceleration ramp		S	1-20
Deceleration ramp		S	0-20
Startup voltage		%	30-80
Protections			



ADXNB025 SOFT STARTER, ADXNB... TYPE, BASIC VERSION, WITH INTEGRATED BY-PASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 25A

Power supply Protection			No power line, phase loss, frequency out of limits, phase sequence (configurable)
Starter protection			Overtemperature
Functions			Overteinperature
Built-in bypass			2
Built-in display and keypad			Yes
Languages			No
View measurements			No
Torque control			No
Adjustable current limit			No
Dynamic braking			No
Kick Start function			No
Motor overload electronic protection			No
Motor protection PTC input			No
Protection against phase loss			No
			Yes
Protection against phase inversion Protection against locked rotor			Yes
Protection against tocked fold			No
			Yes
Protection against low load			No
Programmable alarm			
Digital inputs			No Yes
Analog inputs			No
Digital outputs			
Analog output			Yes
Monitoring communication			No
Optical port for programming			Optional
Event log			No
Motor hour counter			No
Startup counter			No
Clock calendar			No
Remote external keypad			No
Plug-in version			No
Input and Output			
Digital inputs			
	Number of digital input	Nr.	1
	Digital input type		Volt-free contact
Divited systemate	Digital input functions		Motor start
Digital outputs	Number of digital output	Nr.	2 2 NO contacts
	Digital output arrangement		with the same common, 5A 250VAC AC1 - 5A 30 VDC
Communication interfaces	Digital output functions		Line contactor (Run), TOR (Top Of Ramp)
Communication interface			No
Ambient conditions			

ADXNB025



ADXNB025 SOFT STARTER, ADXNB... TYPE, BASIC VERSION, WITH INTEGRATED BY-PASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 25A

Temperature

Operating temperature			
	min	°C	-20
			+60°C (with
	max	°C	current derating
			>40°C)
Storage temperature			
	min	°C	-30
	max	°C	+80
			1000 without
Max altitude		m	derating of the
			starter current
Relative humidity		%	<80%
Pollution degree			2
Installation category			
Housing			
			Screw-fixing or
Mounting			35mm DIN rail
Mounting			(IEC/EN/BS
			60715)
IP degree of protection			IP20
Dimensions (W x H x D)		mm	45 x 159 x 128.4
Weight		Kg	0.63
Dimensions			

-45 (1.77')-128.4 (5.05') -6.7 (0.26") 0 Ø2.3 (0.09") 666 ۵ ۲ 149 (5.87") 159 (6.26') ۲ 0 🗆 0 000

Certifications and compliance

Compliance		
	CSA C22.2 n° 60947-4-2	
	IEC/EN/BS 60947-1	
	IEC/EN/BS 60947-4-2	
	UL 60947-4-2	
Certificates		
	cULus	
	EAC	
	RCM (pending)	
ETIM classification	n	
ETIM 8.0		EC000640 - Soft starter