



## SOFT STARTER, ADXNF... TYPE, NFC VERSION, WITH INTEGRATED BYPASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A

Product designation Product type designation	on			Soft starter NFC ADXNF
Motor type				Asynchronous
Electrical features				three phase
Supplies voltage				
		Type of system Rated supply voltage auxiliary supply voltage (Us) Rated frequency	V Hz	Three phase 208600VAC 100240VAC 50/60
Rated starter current le			Α	18
Rated motor power	IEC ratings (T≤40°C)			
	120 1411190 (1210 0)	230VAC	kW	4
		400VAC	kW	7.5
		500VAC	KW	11
	UL ratings (T≤40°C)	000 0401/40		_
		220-240VAC 380-415VAC	HP HP	5 10
		440-480VAC	пР HP	10
		550-600VAC	HP	15
Number of controlled p	hases		Nr.	2
Built-in bypass				Yes
Cooling System				Natural or forced (optional)
Rated insulation voltage	e Ui		V	600
Programming interface				
Display				No
Programming with NFC	technology			Yes
Optical port Startup and stop setting	30			No
Startup and stop setting	ys			Voltage ramp
Stop method				Voltage ramp or
Acceleration ramp			S	free-wheel stop 1-20
Deceleration ramp			S S	0-20
Startup voltage			 %	30-80
Protections			70	00 00
Power supply Protection	on			No power line, phase loss, frequency out of limits, minimum and maximum voltage and phase sequence
Starter protection				Overtemperature
-				





SOFT STARTER, ADXNF... TYPE, NFC VERSION, WITH INTEGRATED BYPASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A

Functions			
Built-in bypass			2
Built-in display and keypad			Yes
Languages			No
View measurements			No
Torque control			No
Adjustable current limit			No
Dynamic braking			No
Kick Start function			No
Motor overload electronic protection			No
Motor protection PTC input			No
Protection against phase loss			No
Protection against phase inversion			Yes
Protection against locked rotor			Yes
Protection against thyristor overtemperature			No
Protection against low load			Yes
Programmable alarm			No
Digital inputs			Yes
Analog inputs			Yes
Digital outputs			No
Analog output			Yes
Monitoring communication			No
Optical port for programming			Optional
Event log			No
Motor hour counter			No
Startup counter			No
Clock calendar			No
Remote external keypad			No
Plug-in version			No
Input and Output			
Digital inputs			
	Number of digital input	Nr.	1
	Digital input type		Volt-free contact
BUILD A CO	Digital input functions		Motor start
Digital outputs			•
	Number of digital output	Nr.	2
			2 NO contacts
	Digital autout arrangement		with the same
	Digital output arrangement		common, 5A 250VAC AC1 -
			5A 30 VDC
			Programmable:
	D: 11 1 1 1 1 1		line contactor
	Digital output functions		(Run), TOR (Top
			Of Ramp), alarm
Communication interfaces			
Communication interface			NFC
Ambient conditions			
Temperature			
Operating temperature			
	min	°C	-20
		° <b>^</b>	+60°C (with
	max	°C	current derating >40°C)
			~ <del>4</del> 0 0)






SOFT STARTER, ADXNF... TYPE, NFC VERSION, WITH INTEGRATED BYPASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A

-			
Storage temperature			
	min	°C	-30
	max	°C	+80
			1000 without
Max altitude		m	derating of the
			starter current
Relative humidity		%	<80%
Pollution degree			2
Installation category			III
Housing			
			Screw-fixing or
Mounting			35mm DIN rail
Wounting			(IEC/EN/BS
			60715)
IP degree of protection		•	IP20
Dimensions (W x H x D)		mm	45 x 139 x 113.4
Weight		Kg	0.45
Dimensions			

## Dimensions



## Certifications and compliance

Compliance

CSA C22.2 n° 60947-4-2

IEC/EN/BS 60947-1 IEC/EN/BS 60947-4-2

UL 60947-4-2

Certificates

cULus

EAC

RCM (pending)

## ETIM classification

ETIM 8.0 EC000640 - Soft starter