





Product designation Product type designation Soft Starter ADX...B

Product type designati	on			ADXB
Motor type				Asynchronous
				three phase
Electrical features				
Supplies voltage		Type of ayatam		Three phase
		Type of system Rated supply voltage	V	Three phase 208500VAC
		auxiliary supply voltage (Us)	V	208240VAC
		Rated frequency	Hz	50/60
Rated starter current le	 e	rates inequency	A	110
Rated motor power				
,	IEC ratings (T≤40°C)			
	3 (230VAC	kW	30
		400VAC	kW	55
		500VAC	KW	75
	UL ratings (T≤40°C)			
		220-240VAC	HP	40
		380-415VAC	HP	60
		440-480VAC	HP	75
Number of controlled p	hases		Nr.	3
Built-in bypass				Yes
Cooling System				Forced
Programming interface				
Display				Backlit LCD 2x16
				character
Programming with NFO	2 technology			No
Optical port				No
Startup and stop settin	gs			T
Startup method				Torque or voltage ramp with current
Startup method				limitation
				Torque ramp,
Stop method				voltage ramp,
				free-wheel stop
Draking mathed				DC dynamic with
Braking method				external relay
Protections				
Auxiliary supply protec	tion			Voltage too low
				No power, phase
				loss, phase
Dower aupply Protection	on.			sequence,
Power supply Protection	ווע			frequency out of limits, minimum
				and maximum
				voltage
				-





51ADX0110B

SOFT-MOTORSTARTER 500V 110A, MIT INTEGRIERTEM BYPASS-RELAIS 3 PHASEN

Motor protection		Overload at starting (trip class 2, 10A, 10, 15, 20, 25, 30, 35 and 40), overload during running (trip class 2, 10A, 10, 15, 20, 25 and 30), locked rotor, current asymmetry, minimum torque (dry run),
Starter protection		Overcurrent, overtemperature, bypass failure, phase shorted, temperature sensor fault, maintenance request
Functions Duilt in hymnes		2
Built-in bypass Built-in display and keypad		Yes
Languages		Yes
View measurements		4
Torque control		Yes
Adjustable current limit		Yes
Dynamic braking		Yes
Kick Start function		Yes
Motor overload electronic protection		Yes
Motor protection PTC input		Yes
Protection against phase loss		Yes
Protection against phase inversion		Yes
Protection against locked rotor		Yes
Protection against thyristor overtemperature		Yes
Protection against low load		Yes
Programmable alarm		Yes
Digital inputs		Yes
Analog inputs		Yes
Digital outputs		Yes
Analog output		Yes
Monitoring communication		Yes
Optical port for programming		RS323
Event log		No
Motor hour counter		Yes
Startup counter		Yes
Clock calendar		Yes
Remote external keypad		Yes
Plug-in version		Optional
Input and Output		
Digital inputs		
	Number of digital input Nr.	3 (2 digital inputs + 1 digital/analog input)





SOFT-MOTORSTARTER 500V 110A, MIT INTEGRIERTEM BYPASS-RELAIS 3 PHASEN

Digital input type	24VDC (no need for external feeder) 1 input for start, 1 input programmable (stop, free-wheel
Digital input functions	stopping, external alarm, motor preheat, local control, alarms inhibit, manual resetting of motor thermal protection, keypad lock, second moto
Number of analog input	Nr. 1 (digital/analog) 0-10VDC (0-
Analog input type	20mA with external resistor 500Ω)
Analog input functions	Motor protection via PTC probes, acceleration and/or deceleration ramp via analog input, analog input thresholds for motor starting and stopping, analog input thresholds for programmable relay enable
Number of digital output	Nr. 4
Digital output arrangement	3 x 1 NO (SPST) + 1 C/O (SPDT) Ratings: 5A 250VAC AC1, 2A 250VAC AC15 C/O output for global alarm, 3 x 1NO outputs
Digital output functions	programmable (OFF, motor powered, up to speed, braking, current limit, service required, cascade starting, programmable input thresholds, alarm Axx)
	Number of analog input Analog input type Analog input functions Number of digital output Digital output arrangement

51ADX0110B



SOFT-MOTORSTARTER 500V 110A, MIT INTEGRIERTEM BYPASS-RELAIS 3 PHASEN

Number of analog output Nr.

0...20mA,

Analog output type

Analog output functions

4...20mA (0...10V with external resistor 500Ω) Current, torque, motor thermal

status, power

factor and active power

Ambient conditions

Temperature

Operating temperature

°C min -10

+55°C (with current derating max

>45°C of 1.5%/ °C)

Storage temperature

°C min -30

°C +70 max 1000 without


derating (over Max altitude m 1000mt with current derating of 0.5%/100m)

95% without Relative humidity % condensation or dripping

Pollution degree 3

Housing

Mounting		Screw-fixing
IP degree of protection		IP20
Dimensions (W x H x D)	mm	157 x 584 x 250
Weight	Kg	17.7



TYPE	A	В	С	D	E
ADX 0017B	157 (6.18")	372 (14.64")	223 (8.78")	131 (5.16")	357 (14.05")
ADX 0030B	157 (6.18")	372 (14.64")	223 (8.78")	131 (5.16")	357 (14.05")
ADX 0045B	157 (6.18")	372 (14.64")	223 (8.78")	131 (5.16")	357 (14.05")
ADX 0060B	157 (6.18")	534 (21.02")	250 (9.84")	132 (5.20")	517 (20.35")
ADX 0075B	157 (6.18")	534 (21.02")	250 (9.84")	132 (5.20")	517 (20.35")
ADX 0085B	157 (6.18")	534 (21.02")	250 (9.84")	132 (5.20")	517 (20.35")
ADX 0110B	157 (6.18")	584 (22.99")	250 (9.84")	132 (5.20")	567 (22.32")
ADX 0125B	157 (6.18")	584 (22.99")	250 (9.84")	132 (5.20")	567 (22.32")

Certifications and compliance

Compliance

IEC/EN 60947-1



51ADX0110B

SOFT-MOTORSTARTER 500V 110A, MIT INTEGRIERTEM BYPASS-RELAIS 3 PHASEN

	IEC/EN 60947-4-2	
Certificates		
	CCC	
	EAC	
ETIM classification		
		FC000640 - Soft

ETIM 8.0

EC000640 - Sof starter