



| Product designation Product type designation | | | Soft Starter ADXB Asynchronous |
|---|-------------------------------|-----|--|
| Motor type | | | three phase |
| Electrical features | | | |
| Supplies voltage | | | |
| | Type of system | | Three phase |
| | Rated supply voltage | V | 208500VAC |
| | auxiliary supply voltage (Us) | | 208240VAC |
| | Rated frequency | Hz | 50/60 |
| Rated starter current le | | А | 75 |
| Rated motor power | | | |
| IEC ratings (T≤40°C) | | | |
| | 230VAC | kW | 18.5 |
| | 400VAC | kW | 37 |
| | 500VAC | KW | 45 |
| UL ratings (T≤40°C) | | | |
| | 220-240VAC | HP | 25 |
| | 380-415VAC | HP | 40 |
| | 440-480VAC | HP | 50 |
| Number of controlled phases | | Nr. | 3 |
| Built-in bypass | | | Yes |
| Cooling System | | | Forced |
| Programming interface | | | |
| Display | | | Backlit LCD 2x16 character |
| Programming with NFC technology | | | No |
| Optical port | | | No |
| Startup and stop settings | | | |
| Startup method | | | Torque or voltage ramp with current limitation |
| Stop method | | | Torque ramp, voltage ramp, free-wheel stop |
| Braking method | | | DC dynamic with external relay |
| Protections | | | · |
| Auxiliary supply protection | | | Voltage too low |
| Power supply Protection | | | No power, phase loss, phase sequence, frequency out of limits, minimum and maximum voltage |



| Motor protection | | Overload at starting (trip class 2, 10A, 10, 15, 20, 25, 30, 35 and 40), overload during running (trip class 2, 10A, 10, 15, 20, 25 and 30), locked rotor, current asymmetry, minimum torque (dry run), |
|--|-----------------------------|---|
| Starter protection | | Overcurrent, overtemperature, bypass failure, phase shorted, temperature sensor fault, maintenance request |
| Functions | | |
| Built-in bypass | | 3 |
| Built-in display and keypad | | Yes |
| Languages | | Yes |
| View measurements | | 4 |
| Torque control | | Yes |
| Adjustable current limit | | Yes |
| Dynamic braking | | Yes |
| Kick Start function | | Yes |
| Motor overload electronic protection | | Yes |
| Motor protection PTC input | | Yes |
| Protection against phase loss | | Yes |
| Protection against phase inversion | | Yes |
| Protection against locked rotor | | Yes |
| Protection against thyristor overtemperature | | Yes |
| Protection against low load | | Yes |
| Programmable alarm | | Yes |
| Digital inputs | | Yes |
| Analog inputs | | Yes |
| Digital outputs | | Yes |
| Analog output | | Yes |
| Monitoring communication | | Yes |
| Optical port for programming | | RS323 |
| Event log | | No |
| Motor hour counter | | Yes |
| Startup counter | | Yes |
| Clock calendar | | Yes Yes |
| Remote external keypad Plug-in version | | Optional |
| Input and Output | | |
| Digital inputs | | |
| <u>.</u> | Number of digital input Nr. | 3 (2 digital inputs + 1 digital/analog |

input)




DÉMARREURS PROGRESSIFS AVEC RELAIS BY PASS INTÉGRÉ (SOFT STARTER) 75A 500V 3 PHASES

| Analog inputs | Digital input type Digital input functions | 24VDC (no need for external feeder) 1 input for start, 1 input programmable (stop, free-wheel stopping, external alarm, motor preheat, local control, alarms inhibit, manual resetting of motor thermal protection, keypad lock, second moto |
|-----------------|---|--|
| Analog inputs | Number of analog input | Nr. 1 (digital/analog) 0-10VDC (0- |
| | Analog input type | 20mA with external resistor 500Ω) Motor protection via PTC probes, acceleration |
| | Analog input functions | and/or deceleration ramp via analog input, analog input thresholds for motor starting and stopping, analog input thresholds for programmable relay enable |
| Digital outputs | Number of digital output | Nr. 4 3 x 1 NO (SPST) |
| Analog outputs | Digital output arrangement | + 1 C/O (SPDT) Ratings: 5A 250VAC AC1, 2A 250VAC AC15 C/O output for |
| | Digital output functions | global alarm, 3 x 1NO outputs programmable (OFF, motor powered, up to speed, braking, current limit, service required, cascade starting, programmable input thresholds, alarm Axx) |



DÉMARREURS PROGRESSIFS AVEC RELAIS BY PASS INTÉGRÉ (SOFT STARTER) 75A 500V 3 PHASES

| | | Number of analog output Nr. Analog output type | | | ut Nr. | 1 020 | lmΔ |
|-------------------------|-----------------------|---|-------------|--------------|-------------------------|------------------------------------|--|
| | | | | | 420 with e resist | omA (010) external for 500Ω) | |
| | | , | Analog outp | out functior | าร | motor status | nt, torque, r thermal s, power r and active r |
| Ambient conditions | | | | | | | |
| Temperature | | | | | | | |
| | Operating temperature | | | m | in °C | -10 | |
| | | | | ma | ax °C | currei | C (with nt derating C of 1.5%/ |
| | Storage temperature | | | | | / | |
| | C . | | | m | in °C | -30 | |
| | | | | ma | ax °C | +70 | |
| Max altitude | | | | | m | derati 1000i currei | without ing (over mt with nt derating 5%/100m) |
| Relative humidity | | | | | % | 95% | without ensation or |
| Pollution degree | | | | | | 3 | <u> </u> |
| Housing | | | | | | | |
| Mounting | | | | | | Screv | v-fixing |
| IP degree of protection | 1 | | | | | IP20 | |
| Dimensions (W x H x D |) | | | | mm | 157 x | x 534 x 250 |
| Weight | | | | | Kg | 14.4 | |
| Dimensions | | | | | | | |
| | C C C | ТҮРЕ | A | В | C | D | E |
| 0000 000 | | ADX 0017B | 157 (6.18") | 372 (14.64") | 223 (8.78") | 131 (5.16") | 357 (14.05") |
| | | ADX 0030B | 157 (6.18") | 372 (14.64") | | 131 (5.16") | 357 (14.05") |
| | | ADX 0045B | 157 (6.18") | 372 (14.64") | 223 (8.78") | 131 (5.16") | 357 (14.05") |
| | | ADV 0060D | 157 (C 10") | E04 /04 00") | 050 /0 04" | 100 (F 00") | E17 (00 0E") |



ADX 0060B

ADX 0075B

ADX 0085B

ADX 0110B

ADX 0125B

157 (6.18")

157 (6.18")

157 (6.18")

157 (6.18")

534 (21.02") 250 (9.84")

534 (21.02") 250 (9.84")

584 (22.99") 250 (9.84")

250 (9.84")

534 (21.02")

157 (6.18") 584 (22.99") 250 (9.84")

Certifications and compliance

Compliance

517 (20.35")

517 (20.35")

517 (20.35")

567 (22.32")

567 (22.32")

132 (5.20")

132 (5.20")

132 (5.20")

132 (5.20")

132 (5.20")



| | IEC/EN 60947-4-2 | |
|---------------------|------------------|-----------------|
| Certificates | | |
| | EAC | |
| ETIM classification | | |
| ETIM 8.0 | | EC000640 - Soft |
| | | starter |