electric 软启动器, ADXNB... 型号, 基本型, 带集成旁路继电器, 内置风扇. 辅助电源 100...240VAC. 额定工作电压 208...600VAC, 45A

ENERGY AND AUTOMATION



Product designation
Product type designation

Motor type

Soft starter basic
ADXNB

Asynchronous
three phase

Motor type				three phase
Electrical features				·
Supplies voltage				
		Type of system		Three phase
		Rated supply voltage	V	208600VAC
		auxiliary supply voltage (Us)		100240VAC
		Rated frequency	Hz	50/60
Rated starter current le			Α	45
Rated motor power				
	IEC ratings (T≤40°C)			
		230VAC	kW	11
		400VAC	kW	22
		500VAC	KW	30
	UL ratings (T≤40°C)			
	· , ,	220-240VAC	HP	15
		380-415VAC	HP	25
		440-480VAC	HP	30
		550-600VAC	HP	40
Number of controlled phases			Nr.	2
Built-in bypass	-			Yes
Cooling System				Forced
Rated insulation voltage Ui			V	600
Programming interfac	ee			
				Settings: starting
				voltage,
Potentiometer				acceleration
				ramp,
				deceleration
				ramp
Display				No
Programming with NF	C technology			No
Optical port				No
Startup and stop setting	ngs			
Startup method				Voltage ramp
Stop method				Voltage ramp or free-wheel stop
Acceleration ramp			s	1-20
Deceleration ramp			S	0-20
Startup voltage			<u></u> %	30-80
Protections			/0	JU-00
i Totections				

electric 软启动器, ADXNB... 型号, 基本型, 带集成旁路继电器, 内置风扇. 辅助电源 100...240VAC. 额定工作电

压 208...600VAC, 45A **ENERGY AND AUTOMATION**

Power supply Protection			No power line, phase loss, frequency out of limits, phase sequence (configurable)
Starter protection			Overtemperature
Functions			
Built-in bypass			2
Built-in display and keypad	Yes		
Languages			No
View measurements			No
Torque control			No
Adjustable current limit			No
Dynamic braking			No
Kick Start function			No
Motor overload electronic protection			No
Motor protection PTC input			No
Protection against phase loss			No
Protection against phase inversion			Yes
Protection against locked rotor			Yes
Protection against thyristor overtemperature	No		
Protection against low load	Yes		
Programmable alarm	No		
Digital inputs	No		
Analog inputs	Yes		
Digital outputs	No		
Analog output	Yes		
Monitoring communication	No		
Optical port for programming	Optional		
Event log	No		
Motor hour counter	No		
Startup counter			No
Clock calendar			No
Remote external keypad	No		
Plug-in version			No
Input and Output			INO
Digital inputs			
Digital inputs	Number of digital input	Nr.	1
	Number of digital input	INI.	Volt-free contact
	Digital input type Digital input functions		
Digital autoute	Digital input functions		Motor start
Digital outputs	No selected Patrick and	N.L.	0
	Number of digital output	Nr.	2
			2 NO contacts
	Digital output arrangement		with the same common, 5A
	Digital odtpdt arrangement		250VAC AC1 -
			5A 30 VDC
			Line contactor
	Digital output functions		(Run), TOR (Top
		Of Ramp)	
Communication interfaces			• /
Communication interface	No		
Ambient conditions			



electric 软启动器, ADXNB... 型号, 基本型, 带集成旁路继电器, 内置风扇. 辅助电源 100...240VAC. 额定工作电 压 208...600VAC, 45A


ENERGY AND AUTOMATION

Temperature

Operating temperature

Operating temperature			
	min	°C	-20
			+60°C (with
	max	°C	current derating
			>40°C)
Storage temperature			
	min	°C	-30
	max	°C	+80
			1000 without
Max altitude		m	derating of the
			starter current
Relative humidity		%	<80%
Pollution degree			2
Installation category			III
Housing			
			Screw-fixing or
Mounting			35mm DIN rail
Mounting			(IEC/EN/BS
			60715)
IP degree of protection			IP20
Dimensions (W x H x D)		mm	45 x 159 x 128.4
Weight	_	Kg	0.66

Dimensions



Certifications and compliance

Compliance

CSA C22.2 n° 60947-4-2

IEC/EN/BS 60947-1

IEC/EN/BS 60947-4-2

UL 60947-4-2

Certificates

cULus

EAC

RCM (pending)

ETIM classification

ETIM 8.0

EC000640 - Soft starter