



SOFT STARTER, ADXNB... TYPE, BASIC VERSION, WITH INTEGRATED BY-PASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A

				* L -1
Product designation Product type designati	on			Soft starter basic ADXNB
Motor type				Asynchronous three phase
Electrical features				
Supplies voltage		Time of suntain		Thurshines
		Type of system	V	Three phase 208600VAC
		Rated supply voltage auxiliary supply voltage (Us)	V	100240VAC
		Rated frequency	Hz	50/60
Rated starter current le		Nated frequency	A	18
Rated motor power	,			10
rated motor power	IEC ratings (T≤40°C)			
	120 ramige (12 10 °C)	230VAC	kW	4
		400VAC	kW	7.5
		500VAC	KW	11
	UL ratings (T≤40°C)			
	5	220-240VAC	HP	5
		380-415VAC	HP	10
		440-480VAC	HP	10
		550-600VAC	HP	15
Number of controlled p	phases		Nr.	2
Built-in bypass				Yes
Cooling System				Natural or forced (optional)
Rated insulation voltag	e Ui		V	600
Programming interface	;			
Potentiometer				Settings: starting voltage, acceleration ramp, deceleration ramp
Display				No
Programming with NFC	Ctechnology			No
Optical port	3,			No
Startup and stop settin	qs			
Startup method				Voltage ramp
Stop method				Voltage ramp or free-wheel stop
Acceleration ramp			s	1-20
Deceleration ramp			S	0-20
Startup voltage			%	30-80
Protections				





SOFT STARTER, ADXNB... TYPE, BASIC VERSION, WITH INTEGRATED BY-PASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A

Power supply Protection Starter protection			No power line, phase loss, frequency out of limits, phase sequence (configurable) Overtemperature
Functions			Overtemperature
Built-in bypass			2
Built-in display and keypad			Yes
Languages			No
View measurements			No
Torque control			No
Adjustable current limit			No
Dynamic braking			No
Kick Start function			No
Motor overload electronic protection			No
Motor protection PTC input			No
Protection against phase loss			No
Protection against phase inversion			Yes
Protection against locked rotor			Yes
Protection against thyristor overtemperature			No No
Protection against trynstor overtemperature Protection against low load			Yes
Programmable alarm			No
Digital inputs			No
			Yes
Analog inputs Digital outputs			No No
			Yes
Analog output Manitoring communication			No No
Monitoring communication Optical port for programming			Optional
Event log			No
Motor hour counter			No
			No
Startup counter Clock calendar			No
			No
Remote external keypad			No
Plug-in version Input and Output			INO
Digital inputs			
Digital inputs	Number of digital input	Nr.	1
	Digital input type	INI.	Volt-free contact
	Digital input functions		Motor start
Digital outputs	Digital input functions		Wotor start
Digital outputs	Number of digital output	Nr.	2
	Number of digital output	INI.	2 NO contacts
D	igital output arrangement		with the same common, 5A 250VAC AC1 - 5A 30 VDC
	Digital output functions		Line contactor (Run), TOR (Top Of Ramp)
Communication interfaces			
Communication interface			No
Ambient conditions			





ENERGY AND AUTOMATION


SOFT STARTER, ADXNB... TYPE, BASIC VERSION, WITH INTEGRATED BY-PASS RELAY. AUXILIARY SUPPLY 100...240VAC. RATED OPERATIONAL VOLTAGE 208...600VAC, 18A

Temperature

Ope	erating	tem	pera	ture

Operating temperature			
	min	°C	-20
			+60°C (with
	max	°C	current derating
			>40°C)
Storage temperature			
	min	°C	-30
	max	°C	+80
			1000 without
Max altitude		m	derating of the
			starter current
Relative humidity		%	<80%
Pollution degree			2
Installation category			III
Housing			
			Screw-fixing or
Mounting			35mm DIN rail
Wouthing			(IEC/EN/BS
			60715)
IP degree of protection			IP20
Dimensions (W x H x D)		mm	45 x 139 x 113.4
Weight		Kg	0.45

Dimensions



Certifications and compliance

Compliance

CSA C22.2 n° 60947-4-2 IEC/EN/BS 60947-1 IEC/EN/BS 60947-4-2 UL 60947-4-2

Certificates

cULus EAC RCM (pending)

ETIM classification

ETIM 8.0

EC000640 - Soft starter