

SOFT STARTER, ADXNB... , VERSIUNE DE BAZA, CU RELEU BYPASS INTEGRAT. **electric** ALIMENTARE AUXILIARA 24VAC/DC. TENSIUNE NOMINALĂ DE FUNCȚIONARE 208...600VAC,

ENERGY AND AUTOMATION 6A



			· · ·
Product designation Product type designation			Soft starter basic ADXNB
Motor type			Asynchronous three phase
Electrical features			
Supplies voltage			
	Type of system		Three phase
	Rated supply voltage	V	208600VAC
	auxiliary supply voltage (Us)		24VAC/DC
	Rated frequency	Hz	50/60
Rated starter current le		Α	6
Rated motor power			
IEC ratings (T≤40°C)			
	230VAC	kW	1.1
	400VAC	kW	2.2
	500VAC	KW	3
UL ratings (T≤40°C)			
	220-240VAC	HP	1.5
	380-415VAC	HP	2
	440-480VAC	HP	3
	550-600VAC	HP	5
Number of controlled phases		Nr.	2
Built-in bypass			Yes
			Natural or forced
Cooling System			(optional)
Rated insulation voltage Ui		V	600
Programming interface			
			Settings: starting
			voltage,
Potentiometer			acceleration
Poteritionietei			ramp,
			deceleration
			ramp
Display			No
Programming with NFC technology			No
Optical port			No
Startup and stop settings			
Startup method			Voltage ramp
Stop method			Voltage ramp or free-wheel stop
Acceleration ramp		s	1-20
Deceleration ramp		s	0-20
Startup voltage			30-80
Protections		/0	30 00



SOFT STARTER, ADXNB... , VERSIUNE DE BAZA, CU RELEU BYPASS INTEGRAT. **electric** ALIMENTARE AUXILIARA 24VAC/DC. TENSIUNE NOMINALĂ DE FUNCȚIONARE 208...600VAC,

ENERGY AND AUTOMATION 6A

Power supply Protection Starter protection			No power line, phase loss, frequency out of limits, phase sequence (configurable) Overtemperature
Functions			Overtemperature
Built-in bypass			2
Built-in display and keypad			Yes
Languages			No
View measurements			No
Torque control			No
Adjustable current limit			No
Dynamic braking			No
Kick Start function			No
Motor overload electronic protection			No
Motor protection PTC input			No
Protection against phase loss			No
Protection against phase inversion			Yes
Protection against locked rotor			Yes
Protection against thyristor overtemperature			No No
Protection against trynstor overtemperature Protection against low load			Yes
Programmable alarm			No
Digital inputs			No
			Yes
Analog inputs Digital outputs			No No
			Yes
Analog output Manitoring communication			No No
Monitoring communication Optical port for programming			Optional
Event log			No
Motor hour counter			No
			No
Startup counter Clock calendar			No
			No
Remote external keypad			No
Plug-in version Input and Output			INO
Digital inputs			
Digital inputs	Number of digital input	Nr.	1
	Digital input type	INI.	Volt-free contact
	Digital input functions		Motor start
Digital outputs	Digital input functions		Wotor start
Digital outputs	Number of digital output	Nr.	2
	Number of digital output	INI.	2 NO contacts
D	igital output arrangement		with the same common, 5A 250VAC AC1 - 5A 30 VDC
	Digital output functions		Line contactor (Run), TOR (Top Of Ramp)
Communication interfaces			
Communication interface			No
Ambient conditions			






SOFT STARTER, ADXNB..., VERSIUNE DE BAZA, CU RELEU BYPASS INTEGRAT. **electric** ALIMENTARE AUXILIARA 24VAC/DC. TENSIUNE NOMINALĂ DE FUNCȚIONARE 208...600VAC,

Temperature

Operating temperature			
	min	°C	-20
			+60°C (with
	max	°C	current derating
-			>40°C)
Storage temperature			
	min	°C	-30
	max	°C	+80
			1000 without
Max altitude		m	derating of the
			starter current
Relative humidity		%	<80%
Pollution degree			2
Installation category			III
Housing			
			Screw-fixing or
Mounting			35mm DIN rail
Wouthing			(IEC/EN/BS
			60715)
IP degree of protection			IP20
Dimensions (W x H x D)		mm	45 x 139 x 113.4
Weight		Kg	0.45

Dimensions



Certifications and compliance

Compliance

CSA C22.2 n° 60947-4-2 IEC/EN/BS 60947-1 IEC/EN/BS 60947-4-2 UL 60947-4-2

Certificates

cULus EAC RCM (pending)

ETIM classification

EC000640 - Soft **ETIM 8.0** starter