## INDUSTRIAL RELAY WITH LED STATE INDICATOR AND MECHANICAL ACTUATOR, 230VAC, 7A, 2 C/O CONTACT. FITTING ON SOCKET HR6XS2...




Product designation			INDUSTRIAL
Product type designation			RELAYS HR602C
Contact characteristics			TINOUZC
Contact configuration			2 C/O
Rated insulation voltage Ui IEC/EN		V	500
Rated impulse withstand voltage Uimp		kV	4
IEC Conventional free air thermal current Ith		A	7
Rated current (In)		A	7
Relay control voltage		V	230VAC
Max control voltage  Max controllable power in		V	230 VAC
•	AC-1	W	7
Rated operating power AC-1	AC-1	VV	<u>'</u>
Rated operating power AC-1		VA	1750
Rated operating power AC-15		VA	1730
. •	VAC	١/٨	150
	VAC	VA	150
Single-phase motor control	0) (4 0	1.147	0.07
	OVAC	kW	0.37
Rated operating current DC-1	001		
	30V	Α	12
	110V	A	0.3
	220V	Α	0.1
Minimum switching load		V / mA	5 / 100
Contact impedance		mΩ	100
Contact material			Ag/Ni
Operating times			
Closing		ms	<25
Opening		ms	<25
Operations			
Mechanical life		cycles	20000000
Electrical life AC1		cycles	100000
Coil characteristics			
Average coil consumption AC at 20°C		VA	1.7
Average coil consumption DC at 20°C		W	1.1
Operating range			
CI	osing	% Un	70110
	ening	% Un	2055
Maximum cycle frequency		cycles/h	3600
Mechanical features			
Max socket terminal tightening torque		Nm	0.6
Socket screw tightening tool (cross / flat blade)			PH1 / 4.5mm
Conductor section			
AWG/Kcmil			
	min		20
	max		14




INDUSTRIAL RELAY WITH LED STATE INDICATOR AND MECHANICAL ACTUATOR, 230VAC, 7A, 2 C/O CONTACT. FITTING ON SOCKET HR6XS2...

	IEC			
		min	mm²	0.5
		max	mm²	2.5
Operating position				_
		normal		Any
Fixing				On 35mm DIN rail and with screw
Ambient conditions				
Temperature				
	Operating temperature			
		min	°C	-40
		max	°C	+70
	Storage temperature			
		min	°C	-40
		max	°C	+80
Other features				
Indication				Yes
Mechanical contact po	sition indicator			Yes
Mechanical test actuat	tor			Yes
Dimensions				


## HR60 2C... with socket HR6XS21 - HR6XS22



## HR60 4C... with socket HR6XS41 - HR6XS42




HR60 2C... - HR60 4C... with socket HR6XS21S - HR6XS41S




Wiring diagrams

**ENERGY AND AUTOMATION** 

INDUSTRIAL RELAY WITH LED STATE INDICATOR AND MECHANICAL ACTUATOR, 230VAC, 7A, 2 C/O CONTACT. FITTING ON SOCKET HR6XS2...





## Certifications and compliance

Compliance

IEC/EN 61810

Certificates

CSA

cURus

EAC VDE

ETIM classification

ETIM 8.0

EC001437 -Switching relay