

ENERGY AND AUTOMATION

VOLTAGE MONITORING REALY FOR THREE-PHASE SYSTEM, WITH OR WITHOUT NEUTRAL,
MINIMUM AND MAXIMUM AC VOLTAGE. PHASE LOSS, NEUTRAL LOSS AND INCORRECT
PHASE SEQUENCE, 380...440VAC 50/60HZ

-		9				
	•	1.1	12	13		
		55	10.0	***		-
						100
		-	-			
		4		4	-	-
		34				BOR BOOK

Product designation			Voltage monitoring relays
Product type designation			PMV50N
General characteristics			Minimovena
Description			Minimum and maximum AC voltage, phase loss, neutral loss and incorrect phase sequence relay
Type of system			Three-phase with/without neutral
Power supply			
Auxiliary supply voltage Us			Self powered
Operating voltage range			0.71.2 Ue
Rated frequency		Hz	50/60 ±5%
Power consumption Max		VA	27
Power dissipation Max		W	1.9
Control circut			
Rated voltage to control (Ue)			
	min	VAC	380
	Max	VAC	440
Voltage set-point (%Ue)		0.4	00 05
	min	%	8095
Trinning delay	Max	%	105115
Tripping delay		S	0.120
Resetting time		s 	3
Resetting hysteresis Instantaneous tripping for Ue		70	Voltage <70% Ue
Type of reset			Automatic
Repeat accuracy		%	<±0.1
Tripping time for phase loss		ms	60
Relay outputs		1113	00
Number of relays		Nr.	2
Relay state			Normally energised De- energises at tripping
Contact arrangement			2 changeover SPDT
Rated operational voltage AC (IEC)		VAC	250
Maximum switching voltage		VAC	400
IEC Conventional free air thermal current Ith		Α	8
UL/CSA and IEC/EN 60947-5-1 designation			B300




VOLTAGE MONITORING REALY FOR THREE-PHASE SYSTEM, WITH OR WITHOUT NEUTRAL, MINIMUM AND MAXIMUM AC VOLTAGE. PHASE LOSS, NEUTRAL LOSS AND INCORRECT PHASE SEQUENCE, 380...440VAC 50/60HZ **ENERGY AND AUTOMATION**


Electrical life (with rated	d load)		cycles	100000
Mechanical life			cycles	30000000
Functions			.,	
Modular version				3U
Minimum AC voltage				Yes
Maximum AC voltage				Yes
Natural loss				Yes
Phase loss				Yes
Incorrect phase seque	nce			Yes
Asymmetry				No
Minimum frequency				No
Maximum frequency				No
Programmable via NFC	C tochnology and APP			No
Indications	technology and AFF			INU
muications				1 groon LED for
				1 green LED for power on and
Indication				tripping and 2 red
				LEDs for tripping
Connections				
Terminals type				Screw
Tightening torque for te	erminals			
rigintorning torquo for to	Thinking .	max	Nm	0.8
		max	lbin	7
Conductor cross section	nn	max	10111	
Conductor cross section	AWG/Kcmil			
	AVO/ROTH	min	AWG	24
		Max	AWG	12
	IEC	IVIAX	AWG	12
	IEC	min	mm²	0.2
		min Max	mm²	4
Insulations		IVIAX	111111	4
			V	600
Rated insulation voltage			kV	6
Rated impulse withstan	•			
Operating frequency wi	tnstand voltage		kV	4
Ambient conditions				
Temperature				
	Operating temperature		0.0	00
		min	°C	-20
		max	°C	+60
	Storage temperature			
		min	°C	-30
and the second second		max	°C	+80
Housing	<u>, </u>			
Execution (n° of modul	es)			3
Material				Self-extinguishing polyamide
Mounting				35mm DIN rail (IEC/EN 60715)
IEC degree of protection		IP40 on front; IP20 at terminals		
Dimensions (W x H x D	mm	53.5 x 104.7 x 64.9		
Weight			g	200
Dimensions			3	

ENERGY AND AUTOMATION

VOLTAGE MONITORING REALY FOR THREE-PHASE SYSTEM, WITH OR WITHOUT NEUTRAL, MINIMUM AND MAXIMUM AC VOLTAGE. PHASE LOSS, NEUTRAL LOSS AND INCORRECT PHASE SEQUENCE, 380...440VAC 50/60HZ



Wiring diagrams



Certifications and compliance

Compliance

IEC/EN 60255-5

IEC/EN 61000-6-2

IEC/EN 61000-6-3

Certificates

EAC

ETIM classification

ETIM 8.0

EC001438 -Voltage monitoring relay