

变频器, VT1型, 单相供电200...240VAC (50/60HZ)。内置RS485通讯端口, 内置EMC抑制器, CAT. C2, 0.4KW



Product designation		Variable speed drives
Product type designation		VT104A240
General characteristics		
Rated power supply voltage		200240VAC 50/60Hz
Rated output voltage	VAC	Three-phase 0240VAC 0- 599Hz
Rated output current	Α	2.6
Rated output power	kW	0.4
Rated output power	HP	0.5
EMC filter		Built-in EMC suppressor cat. C2
Communication port		RS485, Modbus- RTU and BACnet
Technical features		
Input type		Single-phase
Rated mains voltage	VAC	200240
Operating mains voltage range	VAC	170264
Rated mains frequency	Hz	50/60
Rated mains current without mains choke		7.2
Output type		Three-phase
Output voltage range	VAC	0240
Output frequency range	Hz	0599
Current overload	%/s	150% for 60s
Apparent output power		1
Brake chopper		No
Cooling System		Natural
Switching frequency		116kHz
Functions		
Motor control modes		V/f linear, V/f quadratic, V/f multi-point, sensorless vector control

ENERGY AND AUTOMATION


变频器, VT1型, 单相供电200...240VAC (50/60HZ)。内置RS485通讯端口, 内置EMC抑制器, CAT. C2, 0.4KW


		Frontal
		potentiometer
		External
		potentiometer
		110kΩ Voltage
		signals: 0
		10VDC Current
Speed reference signals		signals: 0/4
		20mA Buttons on
		front keyboard Door-mount
		keyboard 7
		preset speeds
		via digital inputs
		RS485 port
3-wire control		Yes
S-shape curves		Yes
Slip compensation		Yes
Flying restart		No
Access to DC bus		No
DC braking		Yes
DC injection at start		Yes
PID control		Yes
Sequencer (programmable frequency/time cycles)		Yes
Preset speeds		Yes
Motorpotentiometer		Yes
		Main/alternative
		run command
Different parameter configuration sets		select
		Main/alternative
		frequency
		command select
Parameters changeover function		No
Favorite parameters menu		No
Autotuning		Yes
Safe torque Off (STO) safety function		No
PTC probe input		Yes
		Motor overload
		Drive overload
		Overvoltage
Protections		Undervoltage
		Phase loss
		Overtemperature
		Overspeed
		Multi-pump PID for the control of
		up to 4 VT1
Special funct.		drives in master-
		slave
		configuration
Input and Output		
Number of digital input	Nr.	5
Digital input type		PNP logic
Number of digital output	Nr.	1
Digital output arrangement		1 relay output
		with NO contact




变频器, VT1型, 单相供电200...240VAC (50/60HZ)。内置RS485通讯端口, 内置EMC抑制器, CAT. C2, 0.4KW

Output contacts ratings	S			1A 250VAC, 1A 30VDC
Number of analog inpu	ıt		Nr.	2
Analog input type				1 voltage analog input 010VDC 1 current analog input 0/420mA
Number of analog outp	out		Nr.	1
Analog output type				010VDC
Ambient conditions				
Temperature				
	Operating temperature			
		min	°C	-10
		max	°C	+50
		Current derating		from 40 to 50°C with derating of the output current of 6%/°C
	Storage temperature			
		min	°C	-20
		max	°C	+60
Relative humidity			%	<95
Max altitude			m	3000m (over 1000m derate the rated current by 2%/100m)
Maximum Pollution de	gree			2
Housing				
Installation position				Vertical
IP degree of protection	n			IP20
Dimensions (W x H x I	D)		mm	72 x 141 x 141
Weight			Kg	1
Discounting				







Certifications and compliance

Compliance

Dimensions

CSA 22.2 No. 274

EN 61800-5-1

UL508C

Certificates



VT104A240

变频器, VT1型, 单相供电200...240VAC (50/60HZ)。内置RS485通讯端口, 内置EMC抑制器, CAT. C2, 0.4KW

cULus		
EAC		
RCM		

ETIM classification

ETIM 8.0

EC001857 -Frequency converter =< 1 kV