



		1	
Product designation			Soft Starter
Product type designation			ADXB
Motor type			Asynchronous
			three phase
Electrical features			
Supplies voltage	Turne of ourstam		Three phase
	Type of system Rated supply voltage	V	Three phase 208500VAC
	uxiliary supply voltage (Us)	v	208240VAC
a	Rated frequency	Hz	50/60
Rated starter current le	Rated frequency	A	245
Rated motor power			245
IEC ratings (T≤40°C)			
	230VAC	kW	75
	400VAC	kW	132
	500VAC	KW	160
UL ratings (T≤40°C)			100
	220-240VAC	HP	75
	380-415VAC	HP	150
	440-480VAC	HP	200
Number of controlled phases		Nr.	3
Built-in bypass			Yes
Cooling System			Forced
Programming interface			
Display			Backlit LCD 2x1
			character
Programming with NFC technology			No
Optical port			No
Startup and stop settings			<b>T</b>
Startup method			Torque or voltag ramp with curren
Startup metriou			limitation
			Torque ramp,
Stop method			voltage ramp,
•			free-wheel stop
Braking method			DC dynamic with
			external relay
Protections			
Auxiliary supply protection			Voltage too low
			No power, phase
			loss, phase
Power supply Protection			sequence, frequency out of
			limits, minimum

and maximum voltage



Motor protection	Overload at starting (trip class 2, 10A, 10, 15, 20, 25, 30, 35 and 40), overload during running (trip class 2, 10A, 10, 15, 20, 25 and 30), locked rotor, current asymmetry, minimum torque (dry run),
Starter protection	Overcurrent, overtemperature, bypass failure, phase shorted, temperature sensor fault, maintenance request
Functions	
Built-in bypass	3
Built-in display and keypad	Yes
Languages	Yes
View measurements	4
Torque control	Yes
Adjustable current limit	Yes
Dynamic braking	Yes
Kick Start function	Yes
Motor overload electronic protection	Yes
Motor protection PTC input	Yes
Protection against phase loss	Yes
Protection against phase inversion	Yes
Protection against locked rotor	Yes
Protection against thyristor overtemperature	Yes
Protection against low load	Yes
Programmable alarm	Yes
Digital inputs	Yes
Analog inputs	Yes
Digital outputs	Yes
Analog output	Yes
Monitoring communication	Yes
Optical port for programming	R\$323
Event log	No
Motor hour counter	Yes
Startup counter	Yes
Clock calendar	Yes
Remote external keypad	Yes
Plug-in version	Optional
Input and Output	
Digital inputs	
	3 (2 digital inputs Number of digital input Nr. + 1 digital/analog input)

input)



## **51ADX0245B** SOFTSTARTÉR PRO TĚŽKÝ ROZBĚH (5XIN) S INTEGROVANÝM BY-PASS RELÉ, 254A

	Digital input type		24VDC (no need for external feeder) 1 input for start, 1
	Digital input functions		input programmable (stop, free-wheel stopping, external alarm, motor preheat, local control, alarms inhibit, manual resetting of motor thermal protection, keypad lock, second moto
Analog inputs	Number of analog input	Nr.	1 (digital/analog) 0-10VDC (0-
	Analog input type		20mA with external resistor 500Ω)
	Analog input functions		Motor protection via PTC probes, acceleration and/or deceleration ramp via analog input, analog input thresholds for motor starting and stopping, analog input thresholds for programmable relay enable
Digital outputs	Number of digital output Nr.	Nr.	4 3 x 1 NO (SPST)
	Digital output arrangement		+ 1 C/O (SPDT) Ratings: 5A 250VAC AC1, 2A 250VAC AC15 C/O output for global alarm, 3 x
Analog outputs	Digital output functions		1NO outputs programmable (OFF, motor powered, up to speed, braking, current limit, service required, cascade starting, programmable input thresholds, alarm Axx)

Analog outputs

51ADX0245B

## 51ADX0245B



## SOFTSTARTÉR PRO TĚŽKÝ ROZBĚH (5XIN) S INTEGROVANÝM BY-PASS RELÉ, 254A

		Number of analog output	Nr.	1	
	Analog output Analog output funct			020mA, 420mA (010V with external resistor 500Ω) Current, torque, motor thermal status, power factor and active power	
Ambient conditions				ponol	
Temperature					
	Operating temperature				
		min	°C	-10 +55°C (with	
		max	°C	current derating >45°C of 1.5%/ ℃)	
	Storage temperature				
		min	°C	-30	
		max	°C	+70	
Max altitude			m	1000 without derating (over 1000mt with current derating of 0.5%/100m)	
Relative humidity			%	95% without condensation or dripping	
Pollution degree				3	
Housing					
Mounting				Screw-fixing	
IP degree of protection				IP00	
Dimensions (W x H x D	)		mm	273 x 680 x 310	
Weight			Kg	39.3	
Dimensions					



## **51ADX0245B** SOFTSTARTÉR PRO TĚŽKÝ ROZBĚH (5XIN) S INTEGROVANÝM BY-PASS RELÉ, 254A

A C	-1					
	TYPE	A	В	C	D	E
000	ADX 0142B	273 (10.75")				560 (25.20")
	ADX 0190B	273 (10.75")	680 (26.77")	310 (12.20")	230 (9.05")	640 (25.20")
	ADX 0245B	273 (10.75")	680 (26.77")	310 (12.20")	230 (9.05")	640 (25.20")
INCE						
IEC/EN 60947-1						
EC/EN 60947-4-2						
AC						
					500000	240 Osft
					EC0006	640 - Soft

ETIM 8.0

EC000640 - Soft starter