

ADXNF030 SOFT STARTER, ADXNF... TYPE, NFC VERSION, WITH INTEGRATED BYPASS RELAY. AUXILIARY SUPPLY 24VAC/DC. RATED OPERATIONAL VOLTAGE 208...600VAC, 30A



Product designation			Soft starter NFC
Product type designation			ADXNF
Motor type			Asynchronous three phase
Electrical features			
Supplies voltage			
	Type of system		Three phase
	Rated supply voltage	V	
	auxiliary supply voltage (Us)		100240VAC
	Rated frequency	Hz	50/60
Rated starter current le		А	30
Rated motor power			
IEC ratings (T≤40°C)			
č (, ,	230VAC	kW	7.5
	400VAC	kW	15
	500VAC	KW	18.5
UL ratings (T≤40°C)			
3 ()	220-240VAC	HP	10
	380-415VAC	HP	15
	440-480VAC	HP	20
	550-600VAC	HP	25
Number of controlled phases		Nr.	2
Built-in bypass			Yes
			Natural or forced
Cooling System			(optional)
Rated insulation voltage Ui		V	600
Programming interface			
Display			No
Programming with NFC technology			Yes
Optical port			No
Startup and stop settings			
Startup method			Voltage ramp
Stap mathed			Voltage ramp or
Stop method			free-wheel stop
Acceleration ramp		S	1-20
Deceleration ramp		S	0-20
Startup voltage		%	30-80
Protections			
			No power line,
			phase loss,
			frequency out of
Power supply Protection			limits, minimum
			and maximum
			voltage and phase sequence
Ctarter protection			Quarterer areturn

Starter protection

ADXNF030

Overtemperature



ADXNF030 SOFT STARTER, ADXNF... TYPE, NFC VERSION, WITH INTEGRATED BYPASS RELAY. AUXILIARY SUPPLY 24VAC/DC. RATED OPERATIONAL VOLTAGE 208...600VAC, 30A

Built-in bypass	2
Built-in display and keypad	Yes
Languages	No
View measurements	No
Torque control	No
Adjustable current limit	No
Dynamic braking	No
Kick Start function	No
Motor overload electronic protection	No
Motor protection PTC input	No
Protection against phase loss	No
Protection against phase inversion	Yes
Protection against locked rotor	Yes
Protection against thyristor overtemperature	No
Protection against low load	Yes
Programmable alarm	No
Digital inputs	Yes
Analog inputs	Yes
Digital outputs	No
Analog output	Yes
Monitoring communication	No
Optical port for programming	Optional
Event log	No
Motor hour counter	No
Startup counter	No
Clock calendar	No
Remote external keypad	No
Plug-in version	No
Input and Output Digital inputs	

	Number of digital input	Nr.	1
	Digital input type		Volt-free contact
	Digital input functions		Motor start
Digital outputs			
	Number of digital output	Nr.	2
	Digital output arrangement		2 NO contacts with the same common, 5A 250VAC AC1 -
	Digital output functions		5A 30 VDC Programmable: line contactor (Run), TOR (Top Of Ramp), alarm
Communication interfaces			
Communication interface			NFC
Ambient conditions			
Temperature			
Operating temperature			
	min	°C	-20 +60°C (with
	max	°C	current derating >40°C)

ADXNF030




ADXNF030 SOFT STARTER, ADXNF... TYPE, NFC VERSION, WITH INTEGRATED BYPASS RELAY. AUXILIARY SUPPLY 24VAC/DC. RATED OPERATIONAL VOLTAGE 208...600VAC, 30A

Storage temperature			
	min	°C	-30
	max	°C	+80
			1000 without
Max altitude		m	derating of the
			starter current
Relative humidity		%	<80%
Pollution degree			2
Installation category			
Housing			
Mounting			Screw-fixing or
			35mm DIN rail
			(IEC/EN/BS
			60715)
IP degree of protection			IP20
Dimensions (W x H x D)		mm	45 x 159 x 128.4

Weight

Dimensions



Certifications and compliance

Compliance CSA C22.2 n° 60947-4-2 IEC/EN/BS 60947-1 IEC/EN/BS 60947-4-2 UL 60947-4-2 Certificates CULus EAC RCM (pending) ETIM 0.0 EC000640 - Soft

ETIM 8.0

EC000640 - Soft starter

Kg

0.64